
MD as an FX Loop

Posted by hageir - 2008/03/14 05:18

I always wondered how I'd get multiple outs, but still be able to use the internal effects (they're so good, Rhythm Echo, Gatebox, EQ & Dynamix)
So I ventured into routing;

You kinda "shift" everything to the side, starting at output C to F in the routing table
(BD="C", SD="D", etc.) then you set M3/M4 (or any track where you want to have the input machine) to ="Main Outs".

Create an INP machine, it's fun to play with different machines on seperate channels etc.

Now plug all the C, D, E & F outputs to the inputs on your mixer, plug the AUX sends of your mixer into the inputs of your MD: "A" & "B" then you plug the A/B Outputs of the MD into the AUX Returns.

Now you have full control of all the seperate channels (something has to be mixed together, maybe channels that don't need the effects+dynamics) and you can send them into the MD Master Effects :)

=====